
Dual Channel Monitoring Safety Relay 'MSR10RD'





The MSR10RD 'Minotaur' is a dual channel input safety relay with multiple supply voltages and immediate and delayed outputs especially useful for use with PLC control machines. It monitors contactors, input devices and PLC safety functions. With fail-safe internal monitoring and monitored manual reset, any single detected fault will result in lock-out to a safe state. Featuring 8 N/O + 1N/C outputs and 1 N/O + 1 N/C time delay outputs, internally adjustable from 0.1-10 seconds.

24V AC/DC, 110/230V AC (selectable) Power supply

Monitored manual reset X1-X2 contactor Relay safety outputs 8 N/O + 1 N/O (delav) 1 N/C + 1 N/C (delay) Relay auxiliary outputs Accepts 2 N/C switches Safety input 4A at 250VAC, 3A at 24VDC Switching capacity

-10°C to +55°C Temperature

LED indication Red (power on), Green 1&2 (outputs closed)


Green 3 (delay output on) Fixings 35 mm din rail mounting

Approvals

5106069 440R-F23029 24/110/230V 360.00 351.00 342.00

Dual Channel Monitoring Safety Relay 'MSR11R'





The MSR11R 'Minotaur' is a dual channel input safety relay featuring a monitored manual reset function which prevents loop-out defeating of the reset button. Any attempt at defeat will resulting in lock-out of relay. Available in three voltage versions.

24V AC/DC, 110V AC, 230V AC Power supply Monitored manual reset X1-X2 contactor Relay outputs 3 N/O + 1 N/C Safety input Accepts 2 N/C switches Switching capacity 4A at 250VAC, 3A at 24VDC Temperature -10°C to +55°C

LED indication Red (power on), Green x 2 (outputs closed)


35 mm din rail mounting **Fixings**

Approvals

			Unit Price		
Stock No.	Manf Ref'	Туре	1-4	5-9	10-24
5106087		24VAC/DC	155.00	151.13	147.25
5106090	440R-J23045	110VAC	168.00	163.80	159.60
5106093	440R-J23046	230VAC	168.00	163.80	159.60

Dual Channel Monitoring Safety Relay 'MSR14T'





999	000	9999	22.5

The MSR14T 'Minotaur' is a dual channel input safety relay featuring a monitored automatic reset function, a push button can also be added to the test/reset circuit to give a manual reset. Provides contactor monitoring with 2 N/O + 1 N/C outputs.

24V AC/DC Power supply X1-X2 contactor Monitored manual or auto reset

Relay outputs 2 N/O + 1 N/C Safety input Accepts 2 N/C switches Switching capacity 4A at 250VAC, 3A at 24VDC

Temperature -10°C to +55°C

LED indication Red (power on), Green x 2 (outputs closed)


Fixings 35 mm din rail mounting

Approvals UL, TUV

Clock the man the Type	4 !	5-9	10.24
			10-2-
5106096 440R-L23047 24VDC 127	.00 12	23.83 1	120.65

Dual Channel Monitoring Safety Relay 'MSR15D'





The MSR15RD 'Minotaur' is a dual channel input safety relay with immediate and delayed outputs especially useful for use with PLC control where power must be partially maintained for an active braking sequence, after which all power must be removed. Features 2 N/O + 1N/C instantaneous outputs and 1 N/O off delay output, internally adjustable from 0.1-10 seconds.

Power supply 24V AC/DC X1-X2 contactor Manual or auto reset Relay safety outputs 2 N/O + 1 N/C, 1 N/O (delay) Accepts 2 N/C switches Safety input 4A at 250VAC, 2A at 30VDC Switching capacity

Temperature -10°C to +55°C LED indication

Red (power on), Green 1&2 (outputs closed)

Green 3 (delay output on) Fixings 35 mm din rail mounting

Approvals UL, TUV

				Unit Price		
١	Stock No.	Manf Ref'	Туре	1-4	5-9	10-24
	5106099	440R-M23048	24VAC/DC	200.00	195.00	190.00

335